



M850

System Type Programming Guide

1. Press “I” & “E” simultaneously and hold for 5 seconds. The unit is now in setup mode. The screen will change to “SUPP”
2. Press “I” button once. The screen displays “SYSA”.
3. Press “E” button until “TYPE” is displayed.
4. Press “I” to select the desired phase/wire configuration.
5. Press “E” to change to the desired phase/wire configuration.
6. Press “E” to choose: 1P3, 1P2, 3P3, 3P4, 3P3b, or 3P4b. Press “I” to set. The screen returns to “Type”.
7. Press “E” until “CONF” is displayed. Then, press “I”. Now the display shows “SUPP”.
8. Press “E” until “END” is displayed. Then, press “I”. Now you are out of programming mode.
9. Check the resulting display on the meter for voltage and current to see that the desired numeral is displayed and the decimal is in the proper location.
10. If not, repeat procedure starting with step 1 and check that the proper numbers are programmed into the meter.

Power Measurement and Control Specialists

www.pc-s.com

149 Main Street
Stanhope, NJ 07874
Phone: (800) 523-9194
FAX: (973) 448-1674

78 Blackmoor Fairway Close
Stony Plain, Alberta T7X 2X3
Phone: (877) 962-0557
FAX: (780) 963-0554

8539 Monroe Road
Charlotte, NC 28212
Phone: (704) 535-3357
FAX: (704) 535-6288

118 West 12th Street
Bartlesville, OK 74003
Phone: (862) 258-6974
FAX: (973) 448-1674